

# FACTOR

## GHOST 130 USER MANUAL

### SPECIFICATIONS:

**Performance:** Maximum output of 130 lumens. Maximum runtime of 6 hours, Two brightness levels.

**Size:** Length: 1.57" Diameter: 0.54"

**Weight:** 0.6 oz. (17g) excluding batteries

**Battery:** One 10180 USB rechargeable Li-ion battery (included)

**Includes:** Ghost 130 flashlight, one 10180 battery, user manual, paracord and two spare o-rings

### FEATURES:

- USB Rechargeable
- Utilizes high performance CREE XP-G2 LED with a life of 50,000 hours
- Glass Lens with double-sided anti-reflective coating
- Stainless steel body
- Removable Paracord
- Waterproof to IPX-8, 2 meters for 30 minutes
- Twist the head for switching modes
- Digitally regulated output maintains constant brightness

### OUTPUT & RUNTIMES:

1. Stated performance has been measured according to the international flashlight ANSI/NEMA testing standards. The performance may vary due to different batteries and different environment conditions.
2. The Ghost 130 will only use 10180 rechargeable battery.

ANSI/FSC	Low	High
OUTPUT LUMENS	8	130
RUNTIME	6h	30min
DISTANCE	197ft. (60m)	
MAXIMUM INTENSITY	930cd (Max)	
IMPACT RESISTANCE	1m	
WATERPROOF	IPX-8, underwater 2m	

## **OPERATION:**

Battery is pre-installed in the flashlight and you do not need to remove battery at any time.

### **On/Off**

- Fully tighten the flashlight head to turn the light ON and loosen the flashlight head to turn off.
- There is no momentary on function.

### **Mode Selecting**

- Tighten the flashlight head to switch between the two brightness levels: High→Low. Partial tighten will place the light in low and fully tighten to reach the High.

### **Charging**

1. Remove the flashlight head by twisting the head until it comes off. The USB charging port will be revealed once flashlight head is removed.
2. Locate the charging cable under foam insert in packaging.
3. Insert the USB power cable (included) to the flashlight's USB charging port.
4. A red light will illuminate to indicate recharging has begun
5. When flashlight is fully charged, the indicating light will turn green.
6. Disconnect the USB power adapter and secure the flashlight head over the port.

### **Store and Maintenance**

- To store or pack your flashlight, simply loosen the flashlight head a half turn to avoid accidental turn-on and possible battery leakage.
- See flashlight care instructions on [www.factorEquipment.com](http://www.factorEquipment.com)

## **THE FACTOR OATH**

All Factor employees pledge to support you to the point of satisfaction on all its products. We are committed to making sure our products are functioning as advertised, and all your inquiries are addressed.

## **WARRANTY**

Factor provides a Limited Lifetime Warranty on all its products against defects in materials or workmanship.

### **Unwarrantable**

1. Damage, destruction, disassembly and unauthorized intentional modifications
2. Damage due to improper storage or battery leakage.

## **SERVICE**

1. Contact us by email at [support@factorequipment.com](mailto:support@factorequipment.com) or go to [www.factorequipment.com/contact-support/](http://www.factorequipment.com/contact-support/)
2. Any product update information will be displayed on [www.factorequipment.com](http://www.factorequipment.com). Factor Equipment reserves the right to update its products and communicate these updates via the website.

## **WARNING:**

Please avoid shining this light directly into anyone's eyes. This is a high-intensity lighting device, capable of causing damage to eyes.